



ZW20R

Enerwave ZW20R Z-Wave Wireless 120VAC 20A Tamper Resistant (TR) Duplex Receptacle
W/ Two Free Wall Plates



Feature:

- Perfect Replacement for regular receptacles, 120VAC, 20 Amp.
- Wireless Z-Wave technology (Signal Frequency is 908.42 MHz) created a mesh network for command and control interoperability with other Z-Wave compliant controllers.
- Manual and Remote ON/OFF control of any connected lighting and other electrical load for Z-Wave controlled outlet.
- Tamper-Resistant (TR) receptacles keep you and your families from electrical injuries
- Reduce energy consumption and enjoy Wireless Home Automation
- Enhance the value and technology of your apartment, condominiums and homes.
- Includes two Free wall plates, screwless and standard wall plate

Description:

Enerwave ZW20R Z-wave TR Duplex Receptacle is a perfect wireless manual and remote on/off control replacement of regular receptacles, controlling table and floor lamps, small appliances, fan, etc. This Z-Wave TR Duplex Receptacle provides two different type outlets. One outlet with z-wave mark has programmable functions such as scenes, association, schedule event, etc. It can be added to the Mi Casa Verde Vera3 or any other Z-Wave compliant controllers, and a Blue LED on the face cover indicates the status of the controlled outlet and/or act as a night light. The other outlet with Tamper-Resistant feature provides constant power, helps you and your families prevent electrical injuries. This Z-wave TR Duplex Receptacle meets the 2011 NEC code requirement.

Specification:

Manufacture	Enerwave
Color	White
Voltage	120VAC, 60Hz
Maximum load	20 Amp
Signal Frequency	908.42 Mhz
Range	Up to 100 feet in open-air and line of sight distance, depending on obstacles and blocks
Terminations	3 Terminals for Line, Neutral and Ground
Operation Temperature	32°F – 104°F (0°C -40 °C), Indoor Use
Standards and Compliance	Z-Wave Certified FCC Part 15, Class B UL, CUL Listed
Warranty	2 years