

ZWN-333M

Enerwave ZWN-333M Z-WAVE Wireless Plug-in Smart Meter Appliance Module





Enerwave Home Automation Tel: 949-681-9167 Fax: 949-681-9170 www.enerwaveautomation.com

Features

- One Z-Wave controlled and one always-on AC outlet
- Provides manual/remote ON/OFF control of connected loads
- Interoperable with other Z-Wave enabled devices
- Measures energy usage of any connected appliance/device
- Acts as a Z-Wave repeater to extend the range of Z-Wave network
- Compatible with any incandescent, LED lamp and small electrical device

Description

This ZWN-333M Smart Meter Module is a Z-Wave enabled device and fully interoperable with other Z-Wave certified device, which can report wattage energy usage or kWh energy usage to a Z-Wave gateway. In a Z-Wave network, ZWN-333M can be controlled to turn on/off to save energy, also act as a wireless repeater to retransmit the RF signal from one device to another until the intended device is reached. With a horizontal design, the Smart Meter Module will not block other nearby AC outlets.

Specification

Manufacture	Enerwave
Color	White
Voltage	120VAC, 60Hz
Maximum Load	1000W Incandescent, 1200VA Ballast,
	1800W 15A Resistive, 1/3HP Motor
Siginal Frequency	908.42 MHz
Range	Up to 100 feet line of sight
Operation Temprature	32°F-104°F (0 °C-40 °C), Indoor Use
Standards and Compliance	Z-Wave Certified FCC UL, CUL Listed
Warranty	2 years

05222015 Rev.D